





Version: 001-2012 (EDV 6450542)



DE Im Ruhezustand  
 EN In idle state  
 FR En veille  
 IT In riposo  
 NL In standby-stand  
 ES Modo inactivo  
 PT No descanso  
 DK I hviletilstand  
 SE I vänteläge  
 FI Joutotilassa  
 NO I hviletilstand  
 PL W stanie spoczynku  
 CZ V klidovém stavu  
 RU в режиме покоя



DE Während des Gesprächs  
 EN During call  
 FR Pendant la communication  
 IT In conversazione  
 NL Tijdens gesprek  
 ES Durante la llamada  
 PT Durante uma chamada  
 DK Under opkaldet  
 SE Under pågående samtal  
 FI Puhelun aikana  
 NO Under samtalen  
 PL W trakcie rozmowy  
 CZ Během hovoru  
 RU во время вызова

## EN Short user guide innovaphone IP241

### Display components (see numbering on illustrations)

- 1 Name of active registration
- 2 Own extension number
- 3 Contact field
- 4 Display icons 1
- 5 Date and time
- 6 Display icons 2

### Key functions

| Key                  | In idle state  | During call   |
|----------------------|--|---|
| Menu key<br>         | Opens the menu and leaves the menu confirming changes made | Sets up conference with two active calls                |
| Ok key<br><b>Ok</b>  | Confirms the current selection or entry                    |   |
| Disconnect<br>       | Exit menu, return to home screen                           | Terminates call   |
| Microphone<br>       | Switches ringing tone off                                  | Mute / mute key switches microphone off                 |
| R key<br><b>R</b>    | Displays in-bound call list                                | Sets up a consultation call, switches between two calls |
| Redial<br>           | Displays out-bound call list                               | Forwards the incoming call or active call               |
| Speaker<br>          | Prepares call, picking up a call in hands-free mode        | Listen-in, switch to hands-free mode                    |
| Escape<br><b>Esc</b> | One level back in menu without saving settings             | Disconnect call   |
| Delete<br><b>Del</b> | Deletes last character in editor mode                      |   |

### Actions for incoming calls

**Accept call:** Pick up handset, press to pick up call in hands-free mode.

**Reject call:** Press .

**Call diversion:** Press before accepting the call, enter telephone number for the call diversion and confirm by pressing again.

### Actions in idle state

**Dialling:** Enter telephone number; to dial by name, long press to change to characters and enter name, use arrow keys to select desired name if necessary, pick up handset to initiate call.

**Call completion on missed call:** Press **R**, if necessary press arrow keys to select desired call, pick up handset to initiate call.

**Re-dial:** Press , select entry with arrow keys if necessary and pick up handset to initiate call.

**Send message:** Enter telephone number or name, press , select send message and enter the desired text, send by pressing .

**Set call diversion:** Press , select user setup, select call diversion by entering the target number under the required condition. Press twice to save the setting.

**Set presence:** Press , select user setup and presence. Set required activity and add note as necessary.

### Actions during call

**Change to hands-free:** Keep pressed and hang up.

**Terminate hands-free:** Pick up handset or terminate call by pressing .

**Consultation:** Press **R**, select number or name for consultation call. Terminate consultation with and return to initial call.

**Switch between calls:** Press **R** and set up second call. Double press **R** to switch between calls. Press to terminate calls.

**Transfer:** Press **R** and set up second call. Hang up to connect the two calls to each other.

**Conference:** Set up two calls using the **R** key and switch to conference with . Press again to separate calls or hang up to terminate.

**Quick transfer:** Press **R** and dial target number required. If you hang up before the call is initiated, the caller will hear the ring-tone until the person being called picks up the call.

**Blind transfer:** Press and set up second call. Press once more to connect calls together without the callers being put in the wait queue.

### Actions when initiating a call

**Call completion on busy subscriber:** Initiate call, press when you hear busy tone or call waiting signal, then select recall. The telephone will indicate when the subscriber is available again.

**Call completion on no reply:** Initiate call, press while hearing the ring tone, and select recall. The telephone will indicate when the subscriber is active again.

### Icons in contact field

| Icon | Meaning                           | Icon | Meaning                |
|------|-----------------------------------|------|------------------------|
|      | Call pending                      |      | Presence icon: lunch   |
|      | Call initiated, ringing           |      | Presence icon: meeting |
|      | Connected, conference, wait queue |      | Presence icon: away    |
|      | Presence icon: vacation           |      | Presence icon: busy    |

| EN Icons |   |
|----------|---|
|          | New missed calls                            |
|          | Speaker on                                  |
|          | Microphone on (hands-free)                  |
|          | Handset active (handset off-hook)           |
|          | New message waiting                         |
|          | Ring-back initiated                         |
|          | Number presentation switched off            |
|          | Headset on                                  |
|          | Call diversion activated                    |
|          | Phone locked, can only be unlocked with PIN |
|          | Encrypted telephone connection              |
|          | Ringtone off                                |
|          | Registration successful                     |
|          | Registration failed                         |
|          | Registration on stand-by system             |